

D-Link[®]
Building Networks for People



Install Guide

Version 1.00

DI-LB604

Load Balancing Router

System Requirements

- Ethernet-based Cable or DSL Modem
- Computers with Windows, Macintosh, or Linux-based operating systems with an installed Ethernet adapter
- Internet Explorer Version 6.0 or Netscape Navigator 7.0 and above

Package Contents



**DI-LB604
Load Balancing Router**



**CD-ROM
with
Manual & Installation Guide**



CAT5 Ethernet Cable



5V AC Power Adapter




Using a power supply with a different voltage rating will damage this product and void the warranty.

If any of the above items are missing, please contact your reseller.

Hardware Overview

Front Panel



Back Panel Connections

LAN Ports

These are the connections for Ethernet cables to Ethernet enabled computers.

Power Receptor



WAN Ports

This is for the connection of an Ethernet cable to your Cable or DSL modem.


Reset Button

Pressing this button restores the Router to its original factory default settings.

Connecting The DI-LB604 Load Balancing Router To Your Network

- A. First, connect the power adapter to the receptor at the back panel of the DI-LB604 and then plug the other end of the power adapter to a wall outlet or power strip. The Power LED will turn ON to indicate proper operation.
- B.
 1. Power off your Cable or DSL modem; some devices may not have an on/off switch and will require you to unplug the power adapter. Now, the DI-LB604 should be powered on and the Cable/DSL modem should be turned off.
 2. Cable/DSL modem (**Power Off**) – DI-LB604 (**Power On**)
Connect an Ethernet cable to the Ethernet jack located on the Cable/DSL modem. After the Ethernet cable is securely connected, power on the Cable/DSL modem by turning on the unit or plugging in the power adapter.
 3. Cable/DSL modem (**Power On**) – DI-LB604 (**Power On**)
Insert the other end of the Ethernet cable to the WAN PORT on the back panel of the DI-LB604. The WAN LED light will illuminate to indicate proper connection. If the WAN LED is not illuminated, please go back to step B1 and repeat the instructions.
- C. Insert an Ethernet cable to LAN port 1 on the back panel of the DI-LB604 and an available Ethernet port on the network adapter in the computer you will use to configure the DI-LB604. The LED light for LAN Port 1 will illuminate to indicate proper connection. (Note: The LAN Ports on the DI-LB604 are Auto-MDI/MDIX. Meaning you can use a straight-through or crossover Ethernet cable to the LAN Ports.)

Getting Started



Using The Setup Wizard

Open your Web browser and type **“http://192.168.0.1”** into the URL address box. Then press the **Enter** or **Return** key.



The logon screen will appear.

Type **“admin”** for the username and leave the password field blank.



Click **OK**


Once you have logged in, the **Home** screen will appear.



Click **Run Wizard**

You will see the following screens:

Click **Next**



Set up your new password. You have the option to establish a password for the username "admin".

Click **Next**



Choose your time zone from the drop down list.

Click **Next**



! If you are unsure of which setting to select, please contact your Internet Service Provider.

Select the type of Internet Connection that is attached to WAN1.

Click **Next**



Enter the needed information for the type of connection you have chosen.

Click **Next**



Select the type of Internet connection that is attached to WAN2.

Click **Next**



Enter the needed information for the type of connection you have chosen.



D-Link Building Networks For People

Express Ethernet Network
DL-LB604 Dual-WAN Load Balancing Router

Set WAN2 Dynamic IP Address

If your ISP require you to enter a specific host name, Domain Name or specific MAC address, please enter it in. Click **Next** to continue.

Host Name : (optional)

Domain Name : (optional)

MAC Address : (optional)

Back Next Exit

Click **Next**

Your Setup is Complete!



D-Link Building Networks For People

Express Ethernet Network
DL-LB604 Dual-WAN Load Balancing Router

Setup Completed

The Setup Wizard has completed. Click on **Back** to modify changes or mistakes. Click **Restart** to save the current settings and reboot the DI-LB604.

Back Restart Exit

Click **Next**


To connect to the network, make sure the network adapter in your computer is configured properly. Here's how to configure the network adapter to obtain an IP address automatically for the DI-LB604 Load Balancing Router.




For **Microsoft Windows XP**: Go to **Start > right click on My Network Places > select Properties > Right click on the Network Connection associated with the Ethernet adapter and select Properties** (i.e., D-Link DFE-530TX+).

Click **Internet Protocol (TCP/IP)**

Click **Prop-**



Select **Obtain an IP address automatically**



Click **OK**


For **Apple Macintosh OS X:**

Go to the **Apple Menu** Click on **System Preferences** and Select **Network**


Click on **Network**

Select **Built-in Ethernet** in the Show pull down menu

Select **Using DHCP** in the Configure pull down menu



The IP address information, the Subnet Mask, the Router's IP address and the Ethernet adapter address will appear.



Click on **Apply Now**

Restart your computer (if necessary)

NOTES

NOTES

NOTES

Technical Support

D-Link's website contains the latest user documentation and software updates for D-Link products.

D-Link provides free technical support for customers within the United States and Canada for the duration of the product's warranty period.

U.S. and Canadian customers can contact D-Link Technical Support through our website or by phone.

United States

Telephone

(877) 453-5465

Twenty four hours a day, seven days a week.

World Wide Web

<http://support.dlink.com>

E-mail

support@dlink.com

Canada

Telephone

(800) 361-5265

Monday through Friday, 7:30am to 9:00pm EST.

World Wide Web

<http://support.dlink.ca>

E-mail

support@dlink.ca



Version 1.0
2907LB604A16000

©2005 D-Link Corporation/D-Link Systems, Inc. All rights reserved. D-Link and the D-Link logo are registered trademarks of D-Link Corporation or its subsidiaries in the United States and other countries. Other trademarks are the property of their respective owners. All references to speed are for comparison purposes only. Product specifications, size, and shape are subject to change without notice, and actual product appearance may differ from that depicted herein. Visit www.dlink.com for more details.

DI-LB604 10102005