



2-Port USB KVM Switch

With Built-in Cables

The DKVM-2U 2-port KVM (Keyboard, Video and Mouse) switch is a cost effective device for home and office use. This device allows you to easily control 2 different computers from a single set of keyboard, mouse, and VGA monitor. It includes a 2-port KVM switch and 2 sets of built-in cables for ready connection to 2 computers. This KVM switch supports USB keyboards and mice, provides many easy-to-use features and is perfect for home and the small business.

Cost-effective for PC Users

If you have 2 computers and need to use them at the same time, the DKVM-2U saves you the money and space by allowing you to control your 2 computers from a set of keyboard, monitor and mouse. Or, you may have a better, bigger monitor and want to connect both computers to it, the DKVM-2U allows you to do this. 2 sets of cables are attached to the KVM switch ready for use, dispensing you of the need to prepare separate cables and connect them to the switch.

Versatile Functions

The DKVM-2U utilizes advanced microprocessor emulation to intelligently manage each KVM port. This allows simultaneous boot-up of all attached computers. Auto scan,

audible feedback, and keyboard "Hot Key" make it easy to use this KVM switch. There is also a control button located on the front panel that allows you to switch between the computers.

High Monitor Resolution Support

The DKVM-2U is capable of supporting the most demanding resolutions (VGA, SVGA and Multisync monitors) of up to 2048 x 1536 at 75Hz refresh rate (bandwidth up to 400MHz) without any noticeable degradation in image quality.

Key Features

- 2 KVM ports to control of 2 computers from a single set of monitor, USB keyboard, USB mouse
- Saves desktop space, cost
- Audible feedback for confirmation while switching between computers
- Switching between computers using front panel SELECT button or Hot Key command
- Supports SVGA, VGA, and multi-sync monitors
- Video resolutions up to 2048 x 1536 at 75Hz refresh rate
- No driver required
- Bus-power support, no need to attach external power adapter
- Keyboard and mouse emulation for error-free boot-up
- Microsoft IntelliMouse and Microsoft IntelliMouse Explorer support
- Built-in 1.8m KVM cables with standard connectors for computers connection
- Auto-scan mode every 10 seconds
- 2 LED indicators for each computer
- Automatic recall of CAPS LOCK, NUM LOCK and SCROLL LOCK key's status for each computer

DKVM-2U

Technical Specifications

KVM Switch

Connectors to Computers

- 2 sets of 1.8 m built-in KVM cables, each includes the following:
 - 1 DB-15 male connector (to computer's monitor port)
 - 1 USB 2.0 Type A connector (to computer's USB port)

Connectors to Console

- 1 DB-15 female connector (to console monitor)
- 2 USB female connectors (to console USB keyboard/mouse)

Computer Selection

- (Manually switching back and forth between 2 computers)
- Through Push button
 - Through Hot key
 - Switching confirmation: buzzer sound

Hot Key Menu Functions

- Scroll Lock + Scroll Lock + 1: switch to computer 1
- Scroll Lock + Scroll Lock + 2: switch to computer 2
- Scroll Lock + Scroll Lock + →: switch to next computer
- Scroll Lock + Scroll Lock + ←: switch to previous computer
- Scroll Lock + Scroll Lock + B: beeper ON/OFF
- Scroll Lock + Scroll Lock + M: resets mouse and keyboard
- Scroll Lock + Scroll Lock + S: auto-scan mode every 10 seconds

Diagnostic LEDs

2 port LEDs for 2 connected computers

Physical & Environmental

Power Consumption

5V 70mA

Power Supply

Directly from connected computer's USB port, no external power adapter required

Dimensions

104 (L) x 62 (W) x 28 mm (device only)

Weight

565 grams (device and 2 sets of cables included)

Emission (EMI)

- FCC Class B
- CE Class B
- C-Tick

O.S. Support

- Microsoft Windows 98SE, ME, NT, 2000, XP, NT 2003
- Mac O.S. 9.0 and above

Box Includes

- DKVM-2U switch with 2 built-in sets of 1.8 m KVM cables
- Quick Installation Guide



Ordering Information

DKVM-2U 2-port USB KVM Switch With Built-in KVM Cables

Please specify your order as follows:

IKVM-2U Worldwide packing
BKVM-2U USA packaging

D-Link®

Specifications subject to change without prior notice. D-Link is a registered trademarks and QuickMedia is a trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A	TEL: 1-800-326-1688	FAX: 1-866-743-4905
Canada	TEL: 1-905-8295033	FAX: 1-905-8295223
Europe (U. K.)	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
Germany	TEL: 49-6196-77990	FAX: 49-6196-7799300
France	TEL: 33-1-30238688	FAX: 33-1-30238689
Netherlands	TEL: 31-10-282-1445	FAX: 31-10-282-1331
Belgium	TEL: 32(0)2-517-7111	FAX: 32(0)2-517-6500
Italy	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723
Sweden	TEL: 46-(0)8564-61900	FAX: 46-(0)8564-61901
Denmark	TEL: 45-43-969040	FAX: 45-43-424347
Norway	TEL: 47-23-897189	FAX: 47-22-309085
Finland	TEL: 358-9-2707 5080	FAX: 358-9-2707-5081
Spain	TEL: 34-93-4090770	FAX: 34-93-4910795
Portugal	TEL: 351-21-8688493	
Czech Republic	TEL: 420-(603)-276-589	
Switzerland	TEL: 41-(0)-1-832-11-00	FAX: 41(0)-1-832-11-01
Greece	TEL: 30-210-9914 512	FAX: 30-210-9916902
Luxemburg	TEL: 32-(0)2-517-7111	FAX: 32-(0)2-517-6500
Poland	TEL: 48-(0)-22-583-92-75	FAX: 48-(0)-22-583-92-76
Hungary	TEL: 36-(0)-1-461-30-00	FAX: 36-(0)-1-461-30-09
Singapore	TEL: 65-6774-6233	FAX: 65-6774-6322
Australia	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
India	TEL: 91-022-26526696	FAX: 91-022-26528914
Middle East (Dubai)	TEL: 971-4-3916480	FAX: 971-4-3908881
Turkey	TEL: 90-212-289-56-59	FAX: 90-212-289-76-06
Egypt	TEL: 202-414-4295	FAX: 202-415-6704
Israel	TEL: 972-9-9715700	FAX: 972-9-9715601
Latin America	TEL: 56-2-232-3185	FAX: 56-2-232-0923
Brazil	TEL: 55-11-550-39320	FAX: 55-11-550-39322
South Africa	TEL: 27-12-665-2165	FAX: 27-12-665-2186
Russia	TEL: 7-095-744-0099	FAX: 7-095-744-0099 #350
China	TEL: 86-10-58635800	FAX: 86-10-58635799
Taiwan	TEL: 886-2-2910-2626	FAX: 886-2-2910-1515
Headquarters	TEL: 886-2-2916-1600	FAX: 886-2-2914-6299