

## Quick Installation Guide DIR-120

ETHERNET BROADBAND ROUTER

### Package Contents

If any of the items are missing, please contact your reseller.



DIR-120  
Ethernet Broadband  
Router



CD-ROM  
(Quick Router Setup  
Wizard and Manual)



Ethernet (CAT5  
UTP) Cable



Power Adapter



#### Note :

Using a power supply with a different voltage rating will damage and void the warranty of this product.

Default IP: 192.168.0.1

Default Username: Admin

Default Password:

## Quick Installation

1


Remove the  
D-Link Click and  
Connect CD.



2

A. Be sure your Internet connection is active. DO NOT plug the router in yet.  
B. Insert the Quick Router Setup Wizard CD into your computer.

( OS requirement: WINDOWS 2000/XP.)



C. Click "Install Router"( Follow the instruction on the screen and for more information please click " View Manual")

# Troubleshooting

## 1. How do I configure my DIR-120 router without the CD, or check my Wireless Network Name (SSID) and Wireless Encryption Key?

- Connect your PC to the router using an Ethernet cable.
- Open a web browser and enter the address <http://192.168.0.1>  
The default username is 'admin'. The default password is " (leave the field blank).
- If you have changed the password and can not remember it, you will need to reset the router to set the password back to " (leave the field blank).

## 2. How do I reset my router to factory default settings?

- Ensure the router is powered on.
- Press and hold the reset button on the rear of the device for 20 seconds.

**Note: Resetting the router to factory default will erase the current configuration settings. To re-configure your settings, log into the router as outlined in question 1, then run the Setup Wizard.**

## 3. How do I add a new wireless client or PC if I have forgotten my Wireless Network Name (SSID) or Wireless Encryption Key?

- For every PC that needs to connect to the router wirelessly, you will need to ensure you use the correct Wireless Network Name (SSID) and encryption key.
- Use the web based user interface (as described in question 1 above) to check or choose your wireless settings.
- Make sure you take a note of the settings so that you can enter them into each wirelessly connected PC.

## 4. What can I do if my router is not working correctly?

- The manual contains a full troubleshooting section and can be downloaded from the D-Link website (see below), however there are a few quick steps you can take to try and resolve any issues:
  - Check the LED's on the front of the router. The Power, Wireless and Internet LED should be on. One or more of the LAN LED should flash.
  - Check that all the cables are firmly connected at both ends.
  - Power the router off for 20 seconds, and then power it back on.

## 5. Why can I not get an Internet Connection?

- For Cable users make sure Clone MAC address option is ticked during Wizard installation (or enter the registered MAC) and make sure the service has been enabled/connected and is operational.
- For ADSL users please contact your ISP to make sure the service has been enabled/connected by your ISP and that your ISP username and password is correct.

**Note: If you are unable to connect, see the Troubleshooting chapter of the product manual in the D-Link DIR-120 ETHERNET BROADBAND ROUTER CD.**